


ELECTRICAL CHARACTERISTICS	
CENTER FREQUENCY	914 MHz NOM.
3dB BANDWIDTH	24 MHz NOM.
PASSBAND	902 - 924 MHz
PASSBAND LOSS	<5.0 dB
25 dBA REJECTION	870 - 894 MHz
	929 - 960 MHz
50 dBA REJECTION	DC - 870 MHz
	960 - 2500 MHz
VSWR	1.7:1
IMPEDANCE	50 OHMS
POWER	5 WATTS

COPY

Confidential and Proprietary information of ComNav Engineering Inc. Do Not Duplicate or Use Without Permission. ComNav Engineering Inc. claims Copyright in this document as of the Creation, last revision, and last updated dates. All Rights Reserved.



NOTES:
FILTER IS A BI-DIRECTIONAL CROSS-COUPLED DESIGN.

ENGLISH / METRIC ENGLISH	CHECKED BY				
TOLERANCES UNLESS OTHERWISE SPECIFIED MACHINED SURFACES TO BE 125 OR BETTER REMOVE ALL BURRS	DRAWN BY PBF	A	03MAR99	MJG	DEV. GEN. REV. PER 0955
ENGLISH (INCHES) .XX ±.02 .XXX ±.01	ENGINEER MJG	II	26NOV97	MJG	DEV. INIT. ISS. PER 0468
METRIC (MM) .X ±.25 .XX ±.13	REV	DATE	BY	DCN No.	REMARKS
ANGLES ± 0° 30'	SCALE 2:1	APPLIC: COAXIAL FILTER			
	DATE 04MAR99	TITLE: 6BCR6E-914/C24-D			SHEET NO/OF 1 1
	FINISH: BOARD: TINPLATED COPPER JACKET: NI/SILVER RESONATOR: SILVER			DRAWING No. 0L0069	