


1

ELECTRICAL CHARACTERISTICS	
CENTER FREQUENCY:	881.5 MHz
3 dB BANDWIDTH:	32 MHz NOM
LOSS @ FO:	1.0 dB MAX
PASSBAND:	869-894 MHz
PASSBAND FLATNESS:	1.0 dB MAX
VSWR:	1.5:1 MAX
REJECTION:	55 dBc MIN @ 824-849 MHz
POWER HANDLING:	20 WATTS
IMPEDANCE:	50 OHMS IN/OUT

COPY



NOTES:

1) HIGH IMPEDANCE POINTS: THERE MUST BE A MINIMUM 0.050" OF AIR SPACE BETWEEN GROUND AND HIGH IMPEDANCE POINTS. THIS MAY BE ACCOMPLISHED BY RAISING THE FILTER OR DRILLING OUT THE BOARD.

FOR RECOMMENDED FOOTPRINT SEE FP0076.

HAND OR WAVE SOLDERING.
MAX REFLOW TEMP. 240°C FOR 30 SEC., OR 260°C FOR 15 SEC.

FILTER IS ROHS COMPLIANT.
FILTER MAY BE LABELED OR ETCHED.

Confidential and Proprietary information of ComNav Engineering Inc. Do Not Duplicate or Use Without Permission. ComNav Engineering Inc. claims Copyright in this document as of the Creation, last revision, and last updated dates. All Rights Reserved.

ENGLISH / METRIC ENGLISH	CHECKED BY				
TOLERANCES UNLESS OTHERWISE SPECIFIED MACHINED SURFACES TO BE 125 / OR BETTER REMOVE ALL BURRS	DRAWN BY PBF	II	26MAR14	TLA	DEV. INI. ISS. PER 3779
	ENGINEER MJG	REV	DATE	BY	DCN No. REMARKS
ENGLISH (INCHES) .XX ±.02 .XXX ±.010	METRIC (MM) .X ±.5 .XX ±.25	SCALE 1:1	APPLIC: CERAMIC COAXIAL FILTER		
ANGLES ± 0° 30'	DATE 26MAR14	TITLE: 5BCR12C-881.5/C32-D			
	FINISH: JACKET: NICKEL/SILVER RESONATOR: SILVER	DRAWING No. OL1425		SHEET OF 1 1	